

PONTE 16 FLUSH MOUNT

PRODUCT FEATURES

- Contemporary Modern Style
- Inspired by the Ponte Skyscraper in Johannesburg
- Crafted with three small light modules mounted from the base of a perfect ring
- Produces a punch of downward light



LAMPING

Includes 11.3 watt, 590 delivered lumens, 3000K 90 CRI LED module.
120V dimmable with most LED compatible ELV and TRIAC dimmers.
277V compatible with 0-10V dimmers. Ceiling mount only. 120V or 277V.

Nightshade Black



Nightshade Black

Natural Brass

Nightshade Black
Alt View

Natural Brass Alt
View

ORDERING INFORMATION

700FMPNT	SHAPE OR SIZE	FINISH	LAMP
	16 16	NB NATURAL BRASS	-LED930 INTEGRATED LED 90 CRI 3000K 120V
		B NIGHTSHADE BLACK	-LED930-277 INTEGRATED LED 90 CRI 3000K 277V

700FMPNT _____

JOB NAME _____


NOTES _____



PONTE 16 FLUSH MOUNT



SPECIFICATIONS



HARDWARE MATERIAL	Metal
SHADE MATERIAL	Aluminum or Brass
NET WEIGHT	5 lbs
HEIGHT	2.9in
WIDTH	16in
LENGTH	16in
UP LIGHT / DOWN LIGHT / BOTH?	
WET LISTED	
DAMP LISTED	Yes
DRY LISTED	
WALL / CEILING MOUNT	
GENERAL LISTING	ETL Listed
INCLUDES	

LAMPING SPECIFICATIONS

	LED LAMP	INTEGRATED LED	NON LED	NO LAMP
DELIVERED LUMENS		590		
WATTS		11.3		
MAX WATTAGE PER BULB		11.3W		
INPUT VOLTAGE		120V 277V		
DIMMING TYPE*		ELV, TRIAC 0-10V		
CCT		3000K		
CRI		90 CRI		
LED LIFETIME				
L70		>50000		
AVERAGE BULB HOURS				
FIELD SERVICEABLE LED				
LAMP BASE		Integrated LED		
LAMP SHAPE		Integrated LED		
LAMP INCLUDED?		Y		
WARRANTY**		5 Years		

* Dimming information available at www.techlighting.com/Downloads#dimming

** Visit techlighting.com for specific warranty limitations and details.

T20 / T24 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6.	Yes		
This product can be used to comply with California Appliance Efficiency Standards 2016 Title 20 and may be shipped to and sold in California.	N/A		

* If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.

