

LOW-VOLTAGE PENDANTS

Alina Pendant

DESCRIPTION

Hand-blown Venetian teardrop shaped glass with beautiful clear draw. Includes low-voltage, 50 watt halogen bi-pin lamp or 8 watt, 300 delivered lumen, 3000K, replaceable SORAA® LED module and six feet of field-cutttable cable. Dimmable with low-voltage electronic or magnetic dimmer (based on transformer). Works with SORAA.

INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system. For use on T~TRAK, order FreeJack version and T~TRAK FreeJack Connector (sold separately).

ACCESSORIES & OPTICAL CONTROLS

SORAA® LED Bi-Pin Replacement Pendant Module

WEIGHT

3.08lb / 1.4kg ±



brown

smoke

steel blue

white



smoke

ORDERING INFORMATION

700	SYSTEM	ALI	COLOR	FINISH	LAMP
FJ	FREEJACK		N BROWN	Z ANTIQUE BRONZE	12 VOLT HALOGEN
MP	MONOPOINT		K SMOKE	C CHROME	-LEDS830 12 VOLT LED 80 CRI 3000K
MO	MONORAIL		U STEEL BLUE	S SATIN NICKEL	-24 24 VOLT HALOGEN
MO2	TWO-CIRCUIT MONORAIL		W WHITE		

Note: MP includes 4 Round Flush Canopy.

Chrome not offered on Monorail & Two~Circuit Monorail.



700

FIXTURE

TYPE:

JOB NAME:

NOTES:



©2017 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.