

TAWA ALABASTER ACCENT RECHARGEABLE TABLE LAMP

VISUAL COMFORT & CO.

PRODUCT FEATURES

- An optimal choice for bedrooms, living rooms, studies and offices.
- Available in modern finishes
- 12-14 hours of battery life, allowing use for extended periods without worrying about running out of power
- 5- hour charging time
- Designed with an integrated 3-step touch-dimmer.



Alabaster and Hand Rubbed Antique Brass

LAMPING

Includes 120-240V 2.2 watts, 137 delivered lumens, 90 CRI 2700K LED module. Built-in three way dimming. Hand Rubbed Antique Brass includes cream cable. 6 feet of USB C to C cable. Wall charger included.



Alabaster and Hand Rubbed Antique Brass

ORDERING INFORMATION

SLTB529	COLOR TEMP	COLOR	FINISH
	27 2700K	ALB ALABASTER	HAB HAND RUBBED ANTIQUE BRASS

SLTB529 _____

JOB NAME _____

NOTES _____




TAWA ALABASTER ACCENT RECHARGEABLE TABLE LAMP

VISUAL COMFORT & CO.

SPECIFICATIONS

PRIMARY MATERIAL	Brass
SHADE MATERIAL	Alabaster
NET WEIGHT	5 lbs
HEIGHT	11in
WIDTH	4.5in
LENGTH	4.5in
WET LISTED	
DAMP LISTED	
DRY LISTED	
GENERAL LISTING	ETL Listed
INCLUDES	



LAMPING SPECIFICATIONS

	LED LAMP	INTEGRATED LED	NON LED	NO LAMP
DELIVERED LUMENS		137		
WATTS		2.2		
MAX WATTAGE PER BULB		2.2W		
		120V-240V Integrated 3-Step Touch Dimmer		
CCT		2700K		
CRI		90 CRI		
LED LIFETIME				
L70		>50000		
AVERAGE BULB HOURS				
FIELD SERVICEABLE LED				
LAMP BASE		Integrated LED		
LAMP SHAPE		Integrated LED		
LAMP INCLUDED?		True		
WARRANTY**		1 Year		

* Dimming information available at www.techlighting.com/Downloads#dimming

** Visit techlighting.com for specific warranty limitations and details.

T20 / T24 / JA8 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6 / JA8.	No		
This product can be used to comply with California Appliance Efficiency Standards 2016 Title 20 and may be shipped to and sold in California.			

* If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.

