# TRIMMED HOUSING

### 2" Volta

# WAC LIGHTING

# Responsible Lighting®

#### **SPECIFICATIONS**

**Input:** Universal 120 - 277V AC 50/60 Hz

Standards: ETL & cETL, Chicago Plenum, IC-rated, Airtight (see below for list)

**Dimming:** Electronic Low Voltage (ELV): 100%-5% (120V only)

0-10V: 100%-0% (120 - 277V)

**Emergency:** EM fixtures provided with integral Emergency battery back up with


24" lead wire remote test switch. Provides at least 90 minutes of 8W

illumination during emergency operation.

**Mounting:** New construction housings included with universal mounting

brackets and hanger bars Ceiling cut out (Round): Ø 3 %6" Ceiling cut out (Square): 3 %6" x 3 %6"

See next page for ceiling thickness information





Location:


**Construction:** 20 Gauge cold rolled steel

Warranty: 5 year WAC Lighting product warranty









#### HOUSINGS

Model		Power*	S	N, F,W, A Rating		Emergency Backup		Compatible Trims	
Round New Construction	R2RNT R2RCT	Airtight Airtight, Chicago Plenum	15 22	10W 15W	15W 22W	IC rated IC rated	EM	Emergency backup battery (OPTIONAL)	R2RD2T R2RD1T R2RAT R2RWT R2RPT
Square New Construction	R2SNT R2SCT	Airtight Airtight, Chicago Plenum	15 22	10W 15W	15W 22W	IC rated IC rated	EM	Emergency backup battery (OPTIONAL)	R2SD2T R2SD1T R2SAT R2SWT R2SPT
Remodel	R2BRT	Round or Square	15 22	10W 15W	15W 22W	Non-IC Non-IC		N/A	R2RD2T, R2SD2T R2RD1T, R2SD1T R2RAT, R2SAT R2RWT, R2SWT, R2RPT, R2SPT

\*Power consumption depends on beam angle of the trim.

R2 -

Example: R2RNT-15 or R2RNT-15EM (with Emergency backup battery)

Field Replaceable Driver

**D-R2N3-15** Driver for 15W New Construction Hsg Driver for 22W New Construction Hsg

waclighting.com Phone (800) 526.2588 Fax (800) 526.2585 **Headquarters/Eastern Distribution Center** 44 Harbor Park Drive Port Washington, NY 11050 Central Distribution Center 1600 Distribution Ct Lithia Springs, GA 30122 **Western Distribution Center** 1750 Archibald Avenue Ontario, CA 91760

1

## TRIMMED HOUSING


### 2" Volta

# WAC LIGHTING

# Responsible Lighting®

#### TRIMMED INSTALLATION

		Ceiling Thickness					
Trim Model	Trim Description	1/2"	1"	1 1/2"			
R2RD2T R2SD2T	Downlight	Yes	Yes	Yes			
R2RD1T R2SD1T	Shallow Regressed Downlight	Yes	Yes	Yes			
R2RAT/ R2RPT R2SAT/ R2SPT	Adjustable/ Pinhole	Yes, to 45°	Yes, to 35°	Yes, to 20°			
R2RWT R2SWT	Wall Wash		Yes	No			



#### WOOD AND METAL CEILING INSTALLATION





#### Ceiling Thickness Adapter Trim Trim Model Model 1/2" 1" 1 1/2" Description R2RD2T Downlight Yes Yes N/A R2RD1T R2R-ADP1 Round **R2RWT** Wall Wash N/A Yes Yes Up to1" R2RAT Adjustable/Pinhole Yes, to 45° Yes, to 45° N/A R2RPT R2RD2T Downlight Yes Yes Yes R2RD1T R2R-ADP2 **R2RWT** Wall Wash Round No No No Up to 11/2" **R2RAT** Adjustable/Pinhole Yes, to 30° Yes, to 30° Yes, to 30° R2RPT R2SD2T Downlight N/A Yes Yes R2SD1T R2S-ADP1 **R2SWT** Wall Wash Square Yes Yes N/A Up to1" **R2SAT** Adjustable/Pinhole Yes, to 45° N/A Yes, to 45° R2SPT R2SD2T Downlight Yes Yes Yes R2SD1T R2S-ADP2 Square **R2SWT** Wall Wash No No No Up to 11/2" **R2SAT** Adjustable/Pinhole Yes, to 30° Yes, to 30° Yes, to 30°

#### **WOOD AND METAL CEILING ADAPTERS**



Round

**R2R-ADP1** ½" to 1" ceiling thickness

**R2R-ADP2** 1" to 1½" ceiling thickness

R2S-ADP1 ½"to 1"ceiling thickness
R2S-ADP2 1"to 1½" ceiling thickness

waclighting.com Phone (800) 526.2588 Fax (800) 526.2585 Headquarters/Eastern Distribution Center 44 Harbor Park Drive Port Washington, NY 11050 Central Distribution Center 1600 Distribution Ct Lithia Springs, GA 30122

**R2SPT** 

Western Distribution Center 1750 Archibald Avenue Ontario, CA 91760