

### **AquaSense Battery Powered Faucet**

TAG	

### **Architectural/Engineering Specification:**

Zurn AquaSense® faucets are ideal for high-use applications where durability and hands-free operation are necessary. ADA compliant, battery powered, polished chrome-plated cast brass sensor faucet with infrared proximity sensor for retrofit and new construction. Unit is furnished with a standard 1.5 GPM aerator, and mounting hardware.

Zurn Lead Free products (-XL) is the line of durable, high quality brass faucets and fixtures that are designed and manufactured to comply with Section 1417 of the Safe Drinking Water Act (SDWA) which mandates the weighted average lead content of no more than 0.25% of the wetted surface.

#### **Standard Product Features:**

- · Infrared convergence-type proximity sensor
- · 30 second time out feature
- · Chrome-plated Cast Brass Body
- · In-line filter
- · 4 "AA" batteries
- Inlet for a 1/2" ball riser

## **Suffix Options:**

-ADM	Above Deck Mixer
-ADM-1	Above Deck Mixer w/4" Cover Plate
-ADM-2	Above Deck Mixer w/8" Cover Plate
-CP4	Cover Plate 4"[102] Centers
-CP8	Cover Plate 8"[203] Centers
-DSA	Drug Screening Applications
-FC	Flow Control in base of Spout
-GA	3-1/2" Goosneck Spout
-GC	8" Gooseneck Spout
-H4	Wrist Blade handle for ADM
-IA3	Inlet Adaptor (3/8"[10] compression)
-MV	Temperature Mixing Valve
-SH	Supply Hoses for Mixing Valve
-TMV-1	Thermostatic Mixing Valve for Single Faucets

### **Compliance and Certification:**

- Low-Lead Compliant
- ADA Compliant



XL LEAD FREE







Aerator Options:								
		Flowrate GPM [LpM]	Vandal Resistant	WaterSense* Labeled	Outlet Type			
	-E	1.5[5.7]	✓	✓	Aerator			
	-F	0.5[1.9]	✓		Spray			
	-J	1.5[5.7]	✓	✓	Laminar			
	-K	1.0[3.8]	✓	✓	Laminar			
	-L	1.0[3.8]	<b>√</b>		Aerator			
	-M	0.35[1.3]	✓		Spray			

<sup>\*</sup>This device is WaterSense labeled when used with the appropriate flow rate and certified for residential and private restrooms.

Laminar

# Power Supply Choices (Sold Separately):

-ACA 6 VDC Plug-In Power Converter-HW6 Hardwired Power Converter

#### **Optional Power Supply Accessories:**

-CWB Connector Wire for Plug-In Power Converter

-MJ Mini Junction Box

-N

NOTE: For Hardwire applications furnish P6000-HW6 power converter. Order P6000-HW6 power converter seperately.

The P6000-HW6 and P6000-MJ will power up to 8 sensor faucets.

**Architectural/Engineering Approval** 

The information contained in this document is subject to change without notice. Please contact Zurn for most up to date information.






#### **AquaSense Battery Powered Faucet**


TAG

# **TYPICAL Z6920-XL**

## **AquaSense Battery Powered Faucet**


NOTE: Recommended through hole diameter to properly mount the spout/shank is 1-1/8" to 1-1/4".






# TYPICAL Z6920-XL-ACA

AquaSense Plug-In **Powered Faucet** 





# **TYPICAL Z6920-XL-CWB**

### **AquaSense Hardwire Powered Faucet**

Optional:

\* Optional -MJ mini junction box for connecting up to 8 faucets

NOTE: MUST USE EITHER ZURN P6000-HW6 HARDWIRE POWER **CONVERTER OR ZURN P6000-ACA** PLUG-IN POWER CONVERTER TO **ENSURE PROPER OPERATION, USING** A POWER CONVERTER OTHER THAN **ZURN MAY RESULT IN OPERATION** MALFUNCTION OR UNIT FAILURE.

