TIMMUZ

RG200WS



42" x 19.5" x 23.5" (H x W x D)

20" wide gas range in white with sealed burners; replaces RG200W

Highlights:

Slim 20" width is ideal for any space-challenged kitchen

Sealed burners for safer, cleaner cooking

Classic white-on-white finish includes color-matched knobs and handle

Product Features:

Sealed burners	Four sealed burners with removable cast iron tops ensure safer, cleaner cooking
LP kit included	Unit is set for natural gas but can be converted aftermarket with the included LP kit
Large oven	Full 2.3 cu.ft. interior in slim 20" width
High output burner	Front left burner features 12,500 BTU output for powerful cooking
Two semi-rapid burners	Two right burners operate at 9,500 BTU to handle most heating needs
Low output burner	Rear left burner reaches maximum of 5,000 BTUs to allow more precise heating of sensitive items
Continuous grates	Two sets of grates are removable for easy cleaning, with solid construction to support large pots and pans
Broiler compartment	Drop-down lower compartment offers the ideal conditions for broiling
Push-to-turn knobs	Safety knobs help prevent accidents from turning on the oven or burners







RG200WS Specifications:

Overview		
Height of Cabinet	42.0" (107 cm)	
Width	19.5" (50 cm)	
Depth	23.5" (60 cm)	
Depth with Handle	25.75" (65 cm)	
Depth with door at 90°	43.25" (110 cm)	
Door	White	
Cabinet	White	
US Electrical Safety	CSA	
Canadian Electrical Safety	CSA-C	
Voltage/Frequency	115 V AC/60 Hz	
Weight	130.0 lbs. (59 kg)	
Shipping Weight	145.0 lbs. (66 kg)	
Parts & Labor Warranty	1 Year	
UPC	761101058269	
Gas Range		
Ignition	Spark	
LP Convertible	Yes	
Oven Capacity	2.3 cu.ft	
Cooktop Surface	Metal	
Burner Type	Sealed	
Number of Burners	4	
Burner #1 BTU	12000.0	
Burner #2 BTU	9500.0	
Burner #3 BTU	9500.0	
Burner #4 BTU	5000.0	
Burner Controls	Dial	
Oven Controls	Dial	
Backguard	Yes	
Cleaning Type	Manual	
Oven Rack Qty	2	
Oven Interior Height	15.25" (39 cm)	
Oven Interior Width	14.5" (37 cm)	
Oven Interior Depth	17.5" (44 cm)	
Broiler Location	Below Oven	

