


# K A B L E L I T E

## Remote Transformer-300W Mag 24v T20

### DESCRIPTION

This remote magnetic transformer converts standard 120 or 277 volt line-voltage to 24 volts, providing the necessary voltage for powering a MonoRail, Kable Lite, Wall MonoRail or FreeJack low-voltage lighting system. This remote magnetic transformer can be used to power lamps totaling up to 300 watts. This transformer is equipped with fast-acting secondary circuit breaker that will safely turn off the system should a short occur. Once the short has been removed the breaker can be reset.



### INSTALLATION

This transformer must be installed in a remote but accessible location (such as above the ceiling or in a closet). To simplify installation the transformer should be located no more than 20 feet from the run or power feed. The electrician will need to supply the proper gauge conductor from the transformer to the power feed location based on distance (see Low-Voltage Wire Size Table, below).

### OTHER

**Input Wiring:** Can be ordered to hard wire to a junction box or to plug in with 16' power cord with plug. This transformer provides a single 300 watt output and must be used with a single-feed canopy or other power feed option (sold separately). 24 volt output transformers require the use of 24 volt lamps.

LOW-VOLTAGE WIRE SIZE TABLE						
Use to determine the correct THHN wire size for a recommended 3 percent drop in voltage at the specified wattage. The length shown is the length of wire from the transformer to the power feed.						
24 Volt	5 ft.	6-15 ft.	16-20 ft.	21-40 ft.	41-60 ft.	61-90 ft.
300 Watt	#14 GA	#12 GA	#10 GA	#6 GA	#6 GA	#4 GA

### WEIGHT

9.02-6lb / 4.09-2.72kg ±



remote  
transformer-300w  
mag 24v

### ORDERING INFORMATION

700AT3024 FINISH

BLACK

VOLTAGE

T 120V IN/24V OUT  
T277 277V IN/24V OUT



**TECH LIGHTING®**

7400 Linder Avenue  
Skokie, Illinois 60077

T 847.410.4400  
F 847.410.4500

Tech Lighting, L.L.C.

700AT3024 \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_



©2020 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.